



SIGNAL ANTENNA SYSTEMS

WR90-081200-RA-1000:

WR-90 Waveguide to Coax Adapter

WR90-081200-RA-1000: waveguide to coaxial adapter operating in the X-Band frequency range from 8.2 to 12.4 GHz. WR-90 Square type flange and SMA Female coaxial interface compatible with 2.92mm and 3.5mm connectors. Solid aluminum body construction.



PERFORMANCE CHARACTERISTICS

RF and Electrical

Frequency Range	8.2 – 12.4 GHz
VSWR	1.2:1
Power Handling	100 Watts

Mechanical

Size	1.63 x 1.63 x 1.00 (in)
Weight	0.175 lb

Interfaces

Waveguide	WR-90 (Square Cover)
Coaxial	SMA Female

