




SIGNAL ANTENNA SYSTEMS
WR90-EB90-1000:
Waveguide E-Bend Adapter (WR-90)

WR90-EB90-1000: 90-degree (E-plane) waveguide adapter allows for space efficient waveguide turn routing with minimal insertion loss and mismatch.



PERFORMANCE CHARACTERISTICS

RF and Electrical

Frequency Range	8.0 – 12.0 GHz
Insertion Loss	0.08 dB
VSWR	1.2:1
Power Handling	100 Watts

Mechanical

Size	2.0 x 2.0 x 1.63 (in)
Weight	0.16 lb

Interfaces

Waveguide	WR-90 (Square Cover)
-----------	----------------------

